

- **Complex automatic closing mode – Also known as condominium or loop mode.**

This mode is the same as simple automatic closing mode except that only the open limit will stop the opening sequence and only when the automatic closing time has expired will the closing sequence start.

From the closed position;

1. BT trigger starts the opening sequence,
2. Additional BT triggers ignored
3. Open limit stops the opening sequence,
4. Timer starts timing down,
5. Closing sequence begins when time expires,
6. BT trigger stops the closing sequence and immediately the opening sequence begins again.

If a BT trigger or BM trigger is received while the automatic closing timer is counting down , the timer resets and starts counting down again.