

Delay mode -

In some cases swing gates overlap each other. This occurs especially where an electric lock has been fitted. This mode allows for a delay between the starting of the opening and closing sequences of each gate.

Start in closed position:

1. BT trigger starts the opening sequence of motor 1,
2. Opening sequence of motor 2 starts after programmed delay time has expired,
3. Motor 1 open limit stops the opening sequence of motor 1,
4. Motor 2 open limit stops the opening sequence of motor 2,
5. BT trigger or automatic closing starts motor 2 closing sequence.
6. Closing sequence of motor 1 starts after programmed delay time has expired,
7. Motor 2 closed limit stops closing sequence of motor 2.
8. Motor 1 closed limit stops the closing sequence of motor 1.