

- **P.I.R.A.C (Passive infra-red access control) mode –**

This mode is the same as simple automatic closing mode. However in this mode if the BM input is triggered while the opening sequence is running the control card continues opening. After the BM input is cleared while the opening sequence is still running, the control card immediately stops and begins the closing sequence again.

From the closed position;

1. BT trigger starts the opening sequence,
2. BM input triggered and cleared,
3. Opening sequence stops and closing sequence begins,
4. BT trigger stops the closing sequence and immediately the opening sequence begins again.

If the open limit is reached before the BM input is triggered the automatic closing timer will begin running.

If a BT trigger or BM trigger is received while the automatic closing timer is counting down , the timer resets and starts counting down again.