

- Simple automatic closing mode -

In this mode the control card waits for each instruction from the user. However when at any open position, the control card will also wait out the pre-set closing time after which it will start the closing sequence automatically.

From the closed position;

1. BT trigger starts the opening sequence,
2. 2<sup>nd</sup> BT trigger or open limit stops the opening sequence,
3. Timer starts timing down,
4. Closing sequence begins when time expires,
5. BT trigger stops the closing sequence and immediately the opening sequence begins again.

If a BT trigger or BM trigger is received while the automatic closing timer is counting down, the timer resets and starts counting down again.